

Voltage Optimiser

3 Tap (Selectable)
Giv-VO-360



- ◆ Digital display to show the output voltage
- ◆ Built in Voltage protection
- ◆ Prevent wear on appliances caused by electrical over supply and power surges
- ◆ Simple installation
- ◆ Works with, and improves the efficiency of, heat pumps and PV systems
- ◆ Thermal Protection
- ◆ Admendmant 3 compliant
- ◆ Manufactured to the highest British manufacturing standards
- ◆ Saves money on your electricity bills

Specification

3 Tap (Selectable)
Giv-VO-360

Description	GIV-VO-360 Domestic Voltage Optimisation Unit
Input(Volts)	Nominal input voltage 230v + 10% - 6%, 50 Hz, Single Phase AC
Output(Volts)	Nominal input voltage less 6, 12 or 18V (selectable)
Max Load	14.4kW
Dimensions	450mmx280mmx110mm
Weight	Approximately 18kgs
Operating Temperature	-5°c to + 55°c
Terminal Capacity	Incoming Both Live and Neutral=35.0mm2 Outgoing Both Live and Neutral=35.0mm2
Miniature Circuit Breaker	63Amp 6kA Type to BS EN 60898
Enclosure	Mild Steel Power Coated
Ingress Protection	IP20
Cable Entry	Bottom - 2x25mm compression glands
Standards	MCBs to BS EN 60898
Warranty	The Giv-VO-360 voltage optimisation unit is guaranteed for a period of 5 years from date of purchase. This warranty is limited the replacement of faulty components only.



Voltage
Reduced &
Stabilised



Electricity
bills cut



GivEnergy®